

HYBRID DATA TRANSPORT SCHEME OVER OPTICAL NETWORKS

Cross Reference to Related Applications

This application claims the benefit of U.S. Provisional
5 Application No. 60/184,264, filed February 23, 2000, which is
hereby incorporated by reference in its entirety.

The present application may relate to U.S. Serial No.
09/523,574, filed March 10, 2000
~~09/523,574, filed (Attorney Docket No. 0325.00317), U.S.~~
09/523,476, filed March 10, 2000
Serial No. ~~09/523,476, filed (Attorney Docket No.~~
09/535,717, filed March 27, 2000
~~0325.00318), U.S. Serial No. 09/535,717, filed (Attorney~~
09/535,890, filed March 27, 2000
~~Docket No. 0325.00344), and U.S. Serial No. 09/535,890, filed~~
March 27, 2000
~~(Attorney Docket No. 0325.00346), which are hereby~~
incorporated by reference in their entirety.

Field of the Invention

The present invention relates to a method and/or
architecture for hybrid data transportation generally and, more
particularly, to sending a mix of different data types over a fiber
optic network running SONET/SDH framing.

Background of the Invention

Long distance and metropolitan area network (MAN) communications rely on short-haul and long haul fiber optic networks to transport data and telephony traffic. One conventional way to transmit data in fiber networks is through a Synchronous Optical Network/Synchronous Digital Hierarchy (SONET/SDH) protocol. In a SONET/SDH network, data travels in fixed size envelopes that repeat every 125 microseconds. With this synchronous fixed-length framing, every byte (e.g., 8 bits of data) inside a SONET/SDH frame represents a 64 Kbps (64000 bits/sec) channel. The 64 Kbps channel has the same rate as supported by current telephone channels (also called DS0 channels).

SONET was designed to efficiently carry telephony Plesiochronous Digital Hierarchy (PDH) channels such as T1/T3. This was easily achieved by dividing the payload area in fixed slots called virtual tributaries (VT). These virtual tributaries are then grouped together to form higher-rate channels. These fixed slots are efficient for carrying fixed-bandwidth telephony channels because any one or more channels can be added or removed from a bundle without processing an entire payload of channels. Because SONET frames repeat at fixed intervals, these virtual tributaries

0325.00345
CD00025

have fixed locations and time intervals, and it is easy to extract T1/T3 or fractions of T1 without processing the entire SONET payload.

5 With growing volume in data traffic, however, SONET/SDH networks must now carry a significantly large number of data packets - such as ATM (Asynchronous Transfer Mode - 53 bytes each) and IP (Internet Protocol - variable-size packets) in addition to traditional T1/T3 channels. The synchronous framing structure of SONET/SDH that is quite efficient for carrying T1/T3 channels is
10 not able to carry both fixed-bandwidth and variable-bandwidth channels in an optimum way.

SONET/SDH has an inefficient utilization of fiber bandwidth for data packets. For data transport, some of the virtual tributaries ~~that~~ are created for transporting fixed-
15 bandwidth T1 traffic while others are used for transporting packet data packets such as ATM and IP. Since an individual virtual tributary has a limited bandwidth, extra mechanisms have to be used for sending data packets of higher bandwidth using virtual tributaries.

20 In one technique, a 10Mbps data packet channel, for example, is inverse-multiplexed into smaller bandwidth streams and

0325.00345
CD00025

then sent on many virtual tributaries. At the other end, these streams are integrated to reconstruct the full 10Mbps channel. In another method, many of the virtual tributaries are concatenated using hardware to create a higher-bandwidth virtual tributary for transmitting the high-bandwidth data packet.

SONET/SDH lacks of support for data mixing. A SONET fiber link carrying frames containing ATM cells cannot carry POS, because ATM cells frequently carry QoS-sensitive data such as CES (Circuit Emulation Service) or multimedia traffic. Introduction of SONET frames containing POS will cause significant delays (e.g., 125 μ S for each POS frame inserted in the link).

In each of these methods, a unique Path Signal Label (PSL) value in the POH (Path Over-Head) field of ^{the} SONET frame identifies the type of data transmission inside the payload. The payload area is also referred to as SPE (Synchronous Payload Envelope). Because a PSL value identifies contents of ^{the} entire SONET payload envelope, only one type of transmission can be supported at a time in a SONET frame.

One method for data transmission is to use the entire SONET SPE for data packets. The SONET payload area is filled with IP packets using Packet-over-SONET (POS) packets. POS packets are

0325.00345
CD00025

packets by 0x7E (Hexadecimal) at both ends of a packet, with a framing using PPP (Point-to-Point Protocol). Many packets can be put inside a single SONET SPE. This method can only support variable-length packet protocol such as IP. A SONET fiber
5 containing these packets cannot transport T1/T3 channels or real-time streams using ATM cells. The reason for this limitation is that each SONET SPE containing IP packets, for example, introduces a delay of 125 microseconds. Such a delay is not acceptable for T1/T3 circuits or real-time streams using ATM cells.

Another method for data transmission is to use the entire SONET SPE for ATM cells. In this case, ^a SONET SPE is filled with ATM Cells. ATM cells are delimited by their fixed length, and are tracked by doing a hunt for their header checksum byte. Services such as T1, Frame Relay, Ethernet, etc. are transported over ATM
10 using standard protocols. This requires complex implementations in hardware and incorporation of ATM service interworking at each service boundary.

Another method for data transmission is to use the virtual tributaries (VT) for data packets and ATM cells. In this
20 method, a SONET SPE is partitioned in many fixed-bandwidth slots called virtual tributaries (VT). For data transport, some of these

0325.00345
CD00025

virtual tributaries may contain T1/T3 type of fixed-bandwidth traffic while others are used for transporting packet data packets such as ATM and IP.

5 Since an individual virtual tributary has a limited bandwidth, extra mechanisms have to be used for sending data packets of higher bandwidth using virtual tributaries. In one technique, a 10Mbps data packet channel, for example, is inverse-multiplexed into smaller bandwidth streams and then sent on many virtual tributaries. At the other end, these streams are
10 integrated to reconstruct the full 10Mbps channel. In another method, many of the virtual tributaries are concatenated using hardware to create a higher-bandwidth virtual tributary for transmitting the high-bandwidth data packet.

15 Each of these methods uses a fixed-bandwidth channel or a set of channels for transmitting network data packets. In each method, bandwidth capacity of the fiber is poorly utilized since network data packets are bursty in nature and average bandwidth utilization is quite low.

20 Referring to FIG. 1, examples of various data types are shown. A set of time-division-multiplexed (TDM) packets 12a-12n, a set of ATM packets 14a-14n and a set of POS packets 16a-16n are

0325.00345
CD00025

shown in connection with a SONET fiber line 18. In a SONET network, only one type of data can be transferred at a time. The data is identified by a unique PSL (path signal label) byte value inside a Path Over-Head (POH) of the TDM packets 12a-12n, ^{the} ATM _A packets 14a-14n, the POS packets 16a-16n, of PDH traffic. The nodes at different points in the SONET fiber line 18 have different types of data to send on the network.

Conventional data communication networks follow a 7-layer stack of OSI (Open Systems Interface) where packets are sent from node to node using a link layer addressing (i.e., layer 2). A physical layer (i.e., layer 1) determines the physical interface for transport. The layer 2 address for Ethernet, for example, is a 6-byte value called MAC (Media Access Control). For ATM (Asynchronous Transfer Mode) a 53-byte cell is used for framing. The ATM cell contains a VPI (Virtual Path Identifier) and VCI (Virtual Connection Identifier) that are used for link layer addressing (layer 2).

For efficient routing and networking topology efficiency, a higher layer of addressing (called layer 3, or network layer) is needed. This is ~~done~~ ^{done for} usually IP (Internet Protocol) or similar other protocols.

0325.00345
CD00025

Nodes on a network use layer 2 addresses to connect to each other, then parse the layer 3 addresses (such as IP addresses) and headers. The layer 3 parsing determines network topology before deciding which route to send the packets. Such parsing is often time-consuming and requires processing by microprocessors and other pieces of hardware logic.

MPLS (Multi-Protocol Label Switching) is a technique where routes that a packet move through are assigned a series of labels (e.g., 20 bits each out of a 32-bit value). The labels are also referred to as route tags. The labels are inserted between layer 2 (address values for Ethernet frames) and layer 3 (network layer values in PPP frames). These labels are changed, added or dropped as the packet travels from node to node. Using MPLS, intermediate nodes simply look at a label value, consult an internal table to determine where to forward the values, and then send the packet out. Using MPLS, intermediate nodes do not have to look at layer 3 values, which results in increased performance.

The MPLS specification provides for MPLS labels that are carried inside a packet. A special protocol identifier ~~to~~ declares the existence of the MPLS labels. In an Ethernet network, MPLS

0325.00345
CD00025

labels are inserted after MAC addresses (and before network layer addresses start).

In Ethernet networks, user data is encapsulated with layer 3 (network layer) addresses, MPLS labels (optional), and layer 2 (data link) addresses as prefixes. The user data is followed by a 16/32-byte Cyclic Redundancy Check (CRC) value. The header CRC field is inserted after the MPLS labels, but before the user data, as shown by the following TABLE 1:

TABLE 1

Layer 2 Addresses		Data	MPLS	Layer 3	User	Error
		Identifier	Labels	addresses	Data	Detection
Destination MAC (6 bytes)	Source MAC (6 bytes)	Protocol Identifier or IEEE802.3 Length Field (2 bytes)	One or more 32- bit words	...Network Layer addresses...	Payload	CRC

For wide area network (WAN) communications, another protocol Point-to-Point Protocol (PPP) is used. Similar to Ethernet, MPLS labels are inserted between PPP protocol identifiers and user data, as shown by the following TABLE 2:

TABLE 2

Frame Boundary	Address	Control Word	PPP Identifier, etc.	MPLS Labels	User Data	Error Detection	Frame Boundary
0111	Address	Control	PPP Network	One or	Payload	CRC	0111

0325.00345
CD00025

1110			ID	more 32- bit words			1110
------	--	--	----	--------------------------	--	--	------

As a packet goes through a network, intermediate nodes identify whether MPLS labels are embedded in the packet. For example, the following steps describe such an operation for Ethernet and PPP protocols:

(i) check the type of the port from which the packet was received;

(ii) for Ethernet, use MAC address comparing logic to look past the first two fields (i.e., source and destination MAC addresses). For PPP, look past the address and control fields to read the protocol identifier to determine the presence of an MPLS ID value;

(iii) check the MPLS protocol ID (identifier). If the ID is present, MPLS labels are inserted between layer 2 and layer 3 addresses;

(iv) consult ^{an} ~~an~~ MPLS label lookup table to determine how to process the packet. Check to see if the top label value has to be swapped with a new label, removed from the label list, or if a new label has to be added;

(v) recompute CRC on the packet since the MPLS value has changed;

(vi) send the packet from an output port determined by the MPLS label lookup table; and

5 (vii) if the output port type is different from input port type, reformat the frame for the protocol supported on the output port.

Referring to FIG. 2, an example of an optical network with multiple protocol end-points 40 is shown. Limitations of current MPLS framing for optical networks are illustrated. While it is essential to have layer 2 addressing preceding all other bytes on the legacy networks such as Ethernet, ATM, and Frame Relay, having such an architecture for optical networking nodes that interconnect different networks is quite expensive and unnecessary.

Consider MPLS is used for label switching packets from network A to network B or network C. Protocol awareness and packet frame conversions are required at every interconnecting node. For example, the router on network A participates with other routers on the network in MPLS label assignments. The router adds labels on the Ethernet packets coming from network A, before sending them on

0325.00345
CD00025

the ATM network. If the packet must go through ATM or frame relay networks protocol conversions are necessary. Additionally, MPLS assignments using current framing mechanism are necessary.

5 When MPLS is used for packet switching across optical networks (such as SONET rings having intermediate nodes) each intermediate node must have extra logic to process the layer 2 headers and the understand specific MPLS labeling. Such processing must be performed for MPLS switching to send each packet. Such processing for every packet on an optical network requires both hardware and software logic for network packet processing at every optical node. Such logic is not only expensive, but can also severely limit packet-processing performance.

Various conventional protocols have been developed to improve bandwidth usage by attempting to partially solve two problems in SONET networking (i) lack of support for data mixing, and (ii) bandwidth reuse limitations. Such conventional protocols have been partially able to achieve additional bandwidth either by creating fatter pipes with VT, by filling payloads with ATM cells carrying different types of data, or by using SONET link as a multi-node access network using Ethernet framing for data packets.

20

0325.00345
CD00025

While virtual tributaries provide an efficient way to transport PDH traffic, allocation of bandwidth for LAN data such as ~~10/100Mbps~~ ^{10/100Mbps} using a SONET fiber containing T1 traffic becomes difficult. To support 10Mbps through Virtual tributaries one has to either dedicate an entire STS-1 (51Mbps) frame, or use several virtual tributary channels and to perform inverse multiplexing.

Virtual concatenation concatenates several VT channels into bigger virtual pipes to carry higher bandwidth traffic. With such a protocol, while some virtual tributaries carry T1/T3 data as usual, others are concatenated for transport of higher bandwidth data traffic such as 10/100Mbps links.

However, virtual concatenation allocates a fixed bandwidth for LAN. Virtual tributaries cannot dynamically adjust bandwidth usage on a packet-by-packet basis. While it is possible to change the concatenated bandwidth through software, such an implementation does not yield much for bandwidth utilization. Bursty LAN traffic bandwidth usage is typically quite low, resulting in significant waste when used over a fixed bandwidth virtual pipe (average use of a 10Mbps link is 20%, and if an entire STS-1 is used the efficiency becomes about 4%). Another problem with virtual concatenation is that while one virtual pipe may be

0325.00345
CD00025

overloaded with traffic, others may be underutilized. Virtual concatenation cannot dynamically adjust network loads on different channels.

Another conventional approach to increase the utilization of SONET bandwidth is to fill the payload area with ATM cells using a technique known as ATM VP (Virtual Path) multiplexing. ATM VP multiplexing encodes packets in ATM cells and then inserts the cells inside a SONET SPE. The ATM VP multiplexer typically utilizes CES to carry DS0/1 PDH traffic.

However, operations, administration and maintenance (OAM) operations of ATM network are different from that of SONET, and management of the two protocols can become difficult. Similarly, ATM network routing and switch-to-switch signaling data paths are different from IP network routes, resulting in network operational complexity.

Network traffic statistics monitoring has shown that a significant percentage (about 45%) of network traffic comprises IP packets with small packet sizes (e.g., around 40 bytes). With IP over ATM (rfc2684 - Multiprotocol Encapsulation over ATM AAL5) payload size slightly exceeds what can fit inside a single ATM cell. Such an arrangement results in transmission of two ATM

0325.00345
CD00025

cells, with the second cell that is mostly ATM overhead and stuffing bytes. This, with other ATM overheads, means having to allocate extra SONET bandwidth for IP transport if ATM is used as a transport protocol.

5 In addition, using ATM for sending different services requires implementation of ATM transport protocols and interworking for all related protocols (such as IP-over-ATM, Frame Relay-ATM Internetworking, circuit emulation, etc.) in the device. Such implementation requires a high level of complexity in hardware and software, resulting in higher costs of manufacturing and operation of networks.

10 Such conventional network architectures are not efficient for transmitting variable-length IP packets that form the majority of data network traffic on the Internet. Data network traffic comprises variable-length IP packets and fixed-length ATM cells (i.e., 53 bytes).

15 As more and more data is being transported on SONET/SDH rings, there is a need to send variable-length packets on pre-existing SONET/SDH networks. These packets originate out of
20 routers and other data access devices. While SONET/SDH networks must transport these data packets, they must also continue to

0325.00345
CD00025

support TDM-style fixed length packets for telephony and leased line applications.

Conventional approaches cannot mix POS with ATM cells in a single SONET SPE. Conventional approaches do not leave some area of the SONET SPE reserved for VTs and others for POS and/or ATM cells.

Limitations of conventional approaches include one or more of the following (i) inability to mix TDM channels with packet-oriented data over SONET/SDH rings due to timing constraints of the TDM channels without a fixed bandwidth virtual tributary mechanism and (ii) limiting data channels sent on fiber carrying T1 lines to Virtual tributaries (since virtual tributaries are of fixed bandwidth, this restriction limits data channels to fixed bandwidth operation).

Therefore, if a SONET SPE is carrying all ATM cells, it cannot carry IP variable-length packets, and vice versa. Such switches route all packets coming at one tributary to another until switching paths are changed through reprogramming.

Conventional approaches do not take into account network loading conditions and do not support dynamic bandwidth provisioning. Conventional approaches also have increased traffic

0325.00345
CD00025

on core links from too much concentration into too few links. Transporting IP traffic over virtual tributary channels that was originally designed for DS0/1/3 connectivity is inefficient. Because VT assignment is fixed, IP transport is not able to take
5 advantage of total available SONET/SDH bandwidth.

In conventional approaches, IP packets are constrained to go through some pre-configured VT channels while other VT channels may be under-utilized. Once a VT channel is dedicated for a particular traffic and is put on a specific circuit-switched path, the topology does not change, even if traffic conditions change.
10

Conventional approaches have the following disadvantages
(i) ATM and Packets are implemented on different rings because of QoS and timing issues; (ii) very high cost for new fiber and SONET equipment for Telco/ISP/MAN; (iii) only one type of packet goes inside a SONET SPE at one time (the remaining bytes of frame on SONET are wasted) (SONET packets go around the entire SONET ring, limiting bandwidth); and/or (iv) the only way to support telephony channels along with data packets is to allocated part of SONET frame for packet data transmissions (which results in an
15 inefficient bandwidth usage).
20

Summary of the Invention

One aspect of the present invention concerns a packet configured to transmit information via a network. The packet may comprise one or more labels configured to control routing of the packet and a payload.

Another aspect of the invention ^{concerns} an apparatus comprising one or more nodes configured to transfer one or more packets. Each of the packets may comprise one or more labels configured to control switching of the one or more packets and a payload. Each node may be configured to transmit and/or receive the one or more packets in response to the one or more labels.

The objects, features and advantages of the present invention include providing a method and/or architecture that may (i) provide a single SONET ring to carry one or more forms of data; (ii) allow a number of forms of data types to operate inside a single SONET SPE; (iii) provide bandwidth reuse at various nodes of a network, (iv) provide intermediate optical networking nodes that may not require additional hardware and/or software to understand and translate protocol formats for transporting packets, (v) allow network nodes to understand protocol frame formats before reading MPLS labels, (vi) allow SONET sub-sections to run at full speed,

0325.00345
CD00025

effectively boosting SONET bandwidth; and/or (vii) provide significant savings in optical networking equipment.

Brief Description of the Drawings

5 These and other objects, features and advantages of the present invention will be apparent from the following detailed description and the appended claims and drawings in which:

FIG. 1 is a detailed block diagram of conventional fiber optics transmission data types;

10 FIG. 2 is a block diagram of a conventional optical network;

FIG. 3 is a block diagram of a preferred embodiment of the present invention;

15 FIG. 4 is a more detailed block diagram of the circuit of FIG. 3;

FIG. 5 is a block diagram of a HDT frame inside a SONET SPE;

FIG. 6 is a detailed block diagram of a protocol independent frame;

20 FIG. 7 is a detailed block diagram of a variable length envelope;

Sub B7

FIG. 8 is a detailed block diagram of a packet of FIG. 8;

FIG. 9 is a more detailed block diagram of a header of

FIG. 8;

FIG. 10 is a flow chart illustrating an operation of the
5 present invention;

FIG. 11 is a flow chart illustrating an operation of the
present invention;

FIG. 12 is a flow chart illustrating an operation of the
present invention;

FIG. 13 is a block diagram illustrating an implementation
of the present invention; and

FIG. 14 is a block diagram illustrating an operation of
the present invention.

Detailed Description of the Preferred Embodiments

The present invention may provide a Hybrid Data Transport
(HDT) protocol that may allow transmission of fixed bandwidth
channels (e.g., T1/T3), variable-bandwidth data sources (e.g.,
ATM), IP and any other protocol data in a single SONET frame using
20 a single fiber network. The protocol of the present invention may
work seamlessly across a mix of SONET and non-SONET networks, and

0325.00345
CD00025

may yield cost savings in fiber infrastructure, equipment, and operation.

With the use of the Hybrid Data Transport (HDT) protocol of the present invention, an existing fiber network may be fully
5 utilized to transport a number of different types of traffic. The present invention may additionally dynamically manage bandwidth usage on a packet-by-packet basis.

The present invention may provide spatial reuse of bandwidth, allocation of PDH bandwidth in 64Kbps increments,
10 protocol-independent MPLS (Multi-Protocol Label Switching) support, and/or seamless operation over point-to-point and ring networks with SONET/SDH, direct data-over-fiber configurations or other network configurations. The present invention may also be
15 applicable to Synchronous Digital Hierarchy (SDH). However, SONET is used as a general description for SONET/SDH networks with similar implementation for SDH networks. Additional details of the operation of the HDT protocol are also described in connection with direct data-over-fiber networks.

Referring to FIG. 3, a block diagram of a system 100 is
20 shown in accordance with a preferred embodiment of the present invention. A more detailed implementation of the system 100 is

0325.00345
CD00025

illustrated in FIG. 4. The system 100 may comprise a number of devices 102a-102n connected to a network backbone 104. FIG. 4 illustrates the addition of a number of chips 106a-106n. The devices 102a-102n may receive T1/T3 signals, ATM signals, and POS signals. The devices 102a-102n may receive data in one or more of the following data transmission media: SONET, SDH, direct data over fiber (e.g., both in point-to-point or ring configuration) with or without SONET/SDH framing and other transmission methods needed to meet the design criteria of a particular implementation.

The system 100 may provide an increase in the data traffic handling capabilities of SONET/SDH networks. The system 100 may implement a design of a SONET/SDH add/drop multiplexer (ADM) (and a SONET/SDH cross-connect) that may function on variable-length packets. With such an approach, IP (or other protocol) packets of different lengths may be (i) added to a SONET/SDH SPE and (ii) terminated at a different network node (e.g., devices 102a-102n).

Referring to FIG. 5, a detailed block diagram of SONET/SDH payload envelope (SPE) 200 is shown. The present invention may embed a header (and/or footer) 202 (e.g., a 32-bit packet header) to create a deterministic packet transport protocol.

0325.00345
CD00025

5 The packet header may comprise a 32-bit payload header 204a-204n
that may precede each frame, regardless of the particular packet
type stored within the frame. The protocol identification may be
implemented as a few header bits configured to denote the
particular type of packet (e.g., ATM, IP, PPP, Frame Relay, etc.)
embedded within the payload portion of a particular frame.
Bandwidth maximization may be implemented with another bit in the
header 202 that may specify whether the packet may be reused by the
intermediate SONET nodes 102a-102n. The SONET framing may be left
unchanged by implementing a single PSL (Path Signal Label) value
206 in a SONET Path Over Head (POH) 208 that is generally able to
specify the various types of packets embedded within the payload of
a particular frame. The system 100 may be directly applicable to
WDM/DWDM Fiber because individual packet framing is independent of
SONET. The system 100 may be also used in IP-over-Fiber networks.

Referring to FIG. 6, an example of a protocol-independent
frame 150 for transportation of MPLS labels is shown. The frame
150 may comprise an identification portion 152, a MPLS label
portion 154, a layer 2 address portion 156, a data identifier
portion 158, a layer 3 portion 160, a user payload portion 162 and
a error detection portion 164. The MPLS label portion 154 may be

0325.00345
CD00025

used for switching packets at nodes and is not part of the payload. The MPLS label portion 154 may comprise one or more 32-bit words (MPLS labels). Implementing the MPLS labels 154 outside the payload may simplify node design.

5 The protocol independent frame 150 may be utilized by SONET/SDH and direct data-over-fiber networks. The protocol-independent frame 150 may be used with the Hybrid Data Transport previously described. The protocol-independent frame 150 may create an encapsulating frame for all types of packets. The MPLS label portion 157 generally precede any other information, such as the layer 2 and the layer 3 addresses 156 and 160 and the payload portion 162. The protocol-independent frame 150 may be used to implement high-speed switching logic at nodes without having to incorporate protocol-specific knowledge for each of the packets.

5 The protocol-independent frame 150 may provide modified encoding for packet transmission over optical networks. The packet identification portion 152 generally identifies the type of packet being carried in the frame 150, followed by the series of MPLS labels 154, if present.

20 In one implementation, all optical networking nodes may be designed with a simple MPLS switching logic (not shown), without

the requirement of protocol awareness/conversion. Optical networking nodes may include a simple de-framing hardware logic for the MPLS labels 154. Layer 2 address portion 156 may not have significance at the entry/exit points of optical networks. The
5 layer 2 address portion 156 may be implemented behind the packet identification portion 152. The packet identification portion 152 may tell what kind of packet is embedded in the frame 150 after the MPLS labels 157.

*Subst
Amend*

The MPLS labels 157 generally follow the packet identification portion 152, therefore, regardless of underlying protocol, an optical networking node may simply read the MPLS labels 157, use hardware/software logic to perform MPLS switching and forward the packet to the next network.

Intermediate optical networking nodes may not need to understand and translate protocol formats for transporting packets. An optical networking node interfacing ATM, frame relay, and Packet-over-SONET protocols may not need to process protocol frames when using MPLS for switching packets across ports.

The present invention may provide significant saving in
20 optical networking equipment because such equipment does not require high-speed protocol-sensitive hardware to process packets

0325.00345
CD00025

and protocol identification in order to access the MPLS labels. The same MPLS switching engine may be implemented at all optical networking nodes without regard to the types of networking protocols supported.

5 The SONET/SDH payload envelope 200 (e.g., transmitted every 125 μ S) divided into variable length packets is shown. The header 202 may comprise one or more of the following parameters:
(i) packet length, (ii) length of CRC (Cyclic Redundancy Check),
(iii) payload identifier header to describe the nature of packet,
(iv) route labels that may help route packet inside network, (v)
payload header CRC, (vi) actual payload, and/or (vii) payloads CRC.

In SONET, a basic unit of transmission is a Synchronous Transport Signal Level 1 (STS-1) or Optical Carrier Level 1 (OC1) signal. Both operate at 51.84 Mbit/s. STS-1 describes electrical signals, and OC1 refers to the same traffic after being converted into optical signals. SONET also allows channels to be multiplexed. An OC12 circuit, for instance, may carry traffic from four OC3 links. An OC12 circuit may also carry a single channel, in which case the line is said to be concatenated. Such circuits
20 may be described as OC3c, OC12c, and so on.

0325.00345
CD00025

Another protocol similar to SONET is Synchronous Digital Hierarchy (SDH), defined by the ITU (International Telecommunication Union) as G.707 (shortly after ANSI formally ratified the T.105 spec for SONET). Although interconnection of SONET and SDH networks may be relatively rare, several new transoceanic telecommunications projects make use of such links.

The system 100 may maximize fiber bandwidth by implementing the Hybrid Data Transport (HDT) Protocol. The HDT protocol may allow dynamic management of packets to maximize bandwidth. The system 100 may allow the transport of different types of data over a single fiber link. With the system 100, IP (or other protocol) packets, Packet-Over-SONET (POS), ATM cells, G.702-based PDH (T1/T3), SRP, Frame Relay, and other types of data may be mixed inside a SONET payload and dynamically and sent on a single fiber (as shown in FIGS. 5 and 6). The system 100 may provide robust scrambling and unified packet transport over ring and point-to-point networks and may be well suited for non-SONET configurations such as point-to-point WDM networks. The SONET SPE 200 may be filled with HDT frames that may carry a wide mix of fixed and variable bandwidth data. The Simple Data Link (SDL) framing protocol prefixes a payload with a 32-bit word, 16 bits of

5 The system 100 may implement a single fiber link that may
be used for sending different kinds of traffic to use the full
capacity of the link. The system 100 may allow VT or sub-VT
channels to be eliminated. ATM cells, IP (and other protocols)
packets, PPP, frame relay, NxDS0, T1/T3 and others may be mixed
inside SPE on a packet-by-packet basis.

T3
-/~~E1~~)
1

20

0325.00345
CD00025

be implemented without terminating the whole link capacity at each node. Destination nodes may indicate a start of the packet inside a SONET payload. Other packets may pass through the node.

5 Direct data-over-fiber configurations (e.g., without SONET framing) may be easily supported with full link monitoring and management. Support may also be provided for variable-size packet SONET add/drop multiplexer (SONET ADM) devices. Variable-size packets may be transported inside a SONET SPE and nodes may cross-connect and add/drop the packets on different ports.

The system 100 may provide protocol-independent transport of MPLS labels. The HDT may provide for transmission of MPLS labels outside of protocol frame (rather than embedding such labels between data link and network layers as in conventional approaches). Intermediate SONET and optical fiber nodes may be used to create switching and add/drop systems without having to become protocol-aware.

20 With provision for MPLS labels transported outside of packets, the HDT may allow setting up of fast-reroute fail-switchover paths over a hybrid of ring and point-to-point networks using MPLS labels, without requiring nodes to be

0325.00345
CD00025

protocol-sensitive. Such an implementation may eliminate the need to provision and reserve completely unused backup paths on SONET rings.

5 In operation, the payload headers 204a-204n may precede every packet to carry the information to support HDT. A uniform structure of the header across a variety of packet types generally simplifies design of optical nodes for packet processing for both SONET and direct data-over-fiber networks. The headers 204a-204n may also contain a reusability bit that is set by the sending node. 10 If the reusability bit is cleared, a destination node may reset the data identification bits to free up the packet area for reuse by new data packet. The packet area may be reused at either at the destination node or other downstream nodes.

By using the payload header 204a-204n to identify the 15 type of a packet, the HDT is generally able to extend data identification beyond PSL-based SPE-level data typing and put multiple data types inside a SONET SPE. A value of 0000 may indicate the packet area (e.g., the length of the packet area is given by the length value in the outside SDL framing) that does not 20 generally contain any useful data and can be reused for storing new data. HDT may easily support traditional PDH and other guaranteed

0325.00345
CD00025

bandwidth channels. In SONET networks, a frame repeats every 125 μ S, resulting in a bandwidth of 64KHz for every byte in the payload. By fixing the starting location of some packets inside the SONET frame, slots may be created for sending TDM-style traffic. Because the packet length is changeable in one-byte increments, such slots may be created in increments of 64KHz. Because packets are dynamically created, fixed bandwidth channels may be created on the fly by clearing the reusability bit in the payload header.

Referring to FIG. 7, a detailed block diagram of the SONET SPE 200 is shown. The SONET SPE 200 may comprise a number of packets 220a-220n and a number of empty packets 222a-222n. The packet payload header 204a of the packet 220a may identify the packet/protocol. The packet payload header 204a may identify a packet type of the packet 220a stored (or transported). The payload header 204a may tell what kind of packet/protocol (such as Ethernet, PPP, IP, Frame Relay, ATM cells, T1, etc.) is inside a payload of the packet 220a. Different protocols may be supported at two ends (e.g., the devices 102a-102n) of a network without the need for provisioning in advance. In contrast, conventional

0325.00345
CD00025

approaches use a protocol over WAN which is usually negotiated between two parties at the ends devices 102a-102n of the WAN link.

5 The payload header 204a may be used to tell whether one or more of the empty packets 222a-222n inside the SONET SPE 200 may be reused at an intermediate node. In contrast, in conventional SONET networks, the entire SONET SPE 200 travels around the ring until removed by the sender. With the system 100, a receiver may mark the SONET SPE 200 as reusable. Nodes on the fiber network 100 may mark different sections of the SONET SPE 200 as reusable by the other nodes 102a-102n.

Provisioning of TDM channels may provide the ability to mark a portion (or many portions) of a SONET SPE payload area as non-reusable. With a non-reusable area, even when a receiver receives the packet, another receiver cannot reuse the packet area. However, the same receiver may reuse the non-reusable area.

20 In general, there is no limit to the order and manner of packet positioning. Any packet may be marked in any fashion to support, for example, a dynamic mix of data and voice (TDM) traffic on a SONET/SDH network. Such an implementation is not possible with current technologies. The present invention may solve the

0325.00345
CD00025

problem of mixed value and data transmissions faced by telephone carriers and data providers.

As SONET frames containing fixed bandwidth channels move around the ring, intermediate nodes may detect these packets (e.g., the reusability bit is reset), note the offsets of these packets, and preserve the respective offsets when recreating the frame (e.g., after adding packets from local input ports) for outbound traffic.

Referring to FIG. 8, a detailed example of a packet is shown. An SDL framing 262 may be in the first 16 bits and may contain the length of the entire payload, including SDL framing bytes. A 16 bits of CRC-16 264 may be provided on the length field (e.g., $x_{16} + x_{12} + x_5 + 1$). The payload header 204a-204n may be a 32-bit word, followed optionally by an OAM bytes or MPLS labels 268. MPLS/OAM bytes may be variable number of MPLS labels or OAM values that may be transmitted in the header area of HDT, outside of payload. A next fragment offset 270 may be a 16-bit value showing the location offset of next packet fragment (if any) of the packet. The next fragment offset 270 is generally taken from the start of current packet. A header CRC 272 may be computed over payload header bytes only, with same scrambling polynomial used for

0325.00345
CD00025

SDL framing. A payload area 274 may contain the actual packet to be transmitted over the WDM or SONET link. The payload area 274 may contain one of a number of types of protocol packets, such as Ethernet, ATM, GR.702, PPP, Frame Relay, etc. A payload CRC 276
5 may be user-controlled value and may be computed for the payload bytes only. The payload CRC 276 is generally either a 16 or 32-bit value, depending on mutual negotiation between sending and receiving stations.

Referring to FIG. 9, various parameters of the packet header 204a are shown. The particular bit width of the payload header 204a may be varied accordingly to meet the design criteria of a particular implementation. A packet identifier 280 (e.g., D3: D0) generally identifies the type of packet in the payload. For example, value of 0000 may represent a null packet. A null packet
10 may indicate that the payload area may be reused. When a packet is dropped at a node, the length field does not generally need to be modified for the packet, only the D3: D0 bits need to be cleared.

A header data area 282 may carry MPLS labels (e.g., outside of payload area). Operation administration and maintenance
15 (OAM) bytes 282 may be used for link management, or any other data separately from the payload. A reusability area 284 (e.g., D7) may

0325.00345
CD00025

be a "1". If a SONET node can reuse a particular packet area, the size of the packet area may be given by the packet length field 264 of the SDL header. If the bit D7 is set to a "0", then a node will not generally mark the packet area as re-usable, even after a
5 packet has been dropped. The particular nodes of the various configuration bits may be varied (e.g., inverted) accordingly to meet the design criteria of a particular implementation.

A header length area 286 (e.g., D15: D8) may include, in one example, a 32-bit payload header. A fragment identifier area 288 (e.g., D17: D16) may be implemented as a two word value. A value of 00 may indicate that the payload area contains a complete packet. A value of 01 may indicate the beginning packet of a fragmentation sequence. A value of 10 may indicate a continuation of packets. A value of 11 may mark the last fragment in the series. Other particular bit patterns may be implemented accordingly to meet the design criteria of a particular implementation.

A padding area 290 (e.g., D18: D19) may indicate a minimum packet length. In one example, the minimum packet length
20 may be 4 bytes (e.g., 2 bytes length + 2 bytes CRC). Idle bytes at the end of packets and elsewhere may be marked by a length field of

0325.00345
CD00025

"0000". In instances there may be less than 4 bytes left between packets. In this case, it may be impossible to place a SDL null packet. Such idle bytes are shown as tail-end padding for the preceding packet. An unused area 292 (e.g., D31:20) may be used
5 for additional expansion.

Referring to FIG. 10, an example of a receive operation is shown. A node may receive a frame at a block 300. A block 302 may determine if the received frame is an HDT frame. The block 302 may use the PSL value in the POH to determine the type of protocol carried inside the SPE. If the PSL shows POS, ATM, or PDH traffic, the receive operation may proceed to the block 304. If no HDT packets are present, a block 306 handles the POS/ATM/PDH packet. If in the block 302, the PSL shows the SPE contains HDT frames, the node uses additional logic for HDT processing to detect and route different types of packets embedded in the SONET SPE 200.

A block 308 may read the POH. A block 310 may determine a first packet of the SONET SPE 200. A block 312 may read a length and CRC of the first packet. A block 314 may determine a match of the length and the CRC. If a non-match of the length and CRC
20 occurs, the receive operation is generally set to a block 316. The block 316 may read a next word of the packet from the SONET SPE

0325.00345
CD00025

318. If a match occurs, the receive operation may process the packet. Once the payload header has been processed and different packet types are been processed and different packet types are identified, hardware (e.g., implemented in the system 100) may use header fields to retrieve the payload and use usual hardware blocks for processing.

ATM cells are generally retrieved by first looking at the PSL value to determine their presence and then reaching the SONET SPE to get fixed byte ATM cells, either with or without HEC-based cell delineation. For example, if the payload header in the HDT shows the payload contains ATM cells, the hardware device generally retrieves payload bytes (up to number of bytes specified in length field) and sends the byte stream to an existing ATM cell processing logic. The ATM cell processing logic may then work on the byte stream using HEC hunting just as if the SPE contained only ATM cells in its payload.

Referring to FIG. 11, an example of a processing operation 320 is shown. A device supporting Hybrid Data Transport HDT protocol generally operates much the same as a normal SONET/SDH transport operates. Operations for processing ATM cells, POS, and PDH protocols are the same and illustrated as processing blocks

0325.00345
CD00025

350, 352 and 354. HDT adds a header to packets to allow their mixing within the same SPE 200. Much of the HDT processing is generally related to processing of the header to identify the type of packet and then passing the starting address of data bytes to standard logic for handling the individual packet type. Support of PDH-type channel typically requires a fixed starting location for the channel in every frame. If PDH support is not needed, packets of any mix may be put anywhere inside the SPE 200 to achieve excellent bandwidth utilization without much operational complexity. When fixed bandwidth channels are carried, some data packets may need to be fragmented when the packet hit a static location. Fragmentation of a packet, however, is generally easily achieved in SONET networking because all bytes in the SPE 200 are transmitted sequentially. Additionally, recovering fragments and putting the fragment together may be simply accomplished.

Referring to FIG. 12, an example of a transmit operation 400 is shown. A device supporting HDT may receive a packet to be transmitted from a system side. In the transmit operation 400, a node may take inputs from different sources 402, encapsulate the packets with an SDL length/CRC fields 404, add an HDT header 406 to each of the packets, and then store the packets inside the SPE.

0325.00345
CD00025

The node may not send a fresh frame on the network in order to transmit the packets. A TDM channel check 408 may determine a reusability of the SPE 200. The transmit operation 400 may reuse available space in an incoming SPE (containing HDT frames). The
5 transmit operation 400 may then may proceed to a length check 410 to see if there is any space available to insert the packet to be sent. If there is enough space, the entire packet is stored (with proper SDL framing and HDT header bytes). Any remaining bytes, depending on the size, are generally either (i) filled with a null
10 HDT packet (e.g., the payload header identification bits are 0000), (ii) filled with SDL null packets (e.g., pairs of length/CRC with a null length field), or (iii) accounted for as tail-end padding (e.g., if the size is less than 4 bytes).

If the transmit operation 400 runs into a fixed-bandwidth channel allocation midway through the packet allocation, the packet is generally fragmented. In this case, a portion of the packet may be stored at one place and other fragments may be stored at another free location. The first fragment offset pointer may contain the starting location of second fragment. Because bytes are
20 transmitted sequentially in the SPE 200, reassembling fragments may be easily achieved.

0325.00345
CD00025

If a particular node detects an incoming SONET frame on a receive port, or if there is a frame in the transmit/receive queue, the node checks the frame to see if there are unused/reusable areas in the incoming/queued frame that can be used for sending data. If there is enough space available in the frame, the node fills the space with additional data before sending the frame out.

In HDT, PDH channels of any bandwidth (up to allowable SONET bandwidth limits) may be provisioned anywhere inside the SONET SPE. To achieve precise timing, PDH bytes must begin at the same offset inside the SONET SPE. However, allocation of PDH channels at different locations inside a SONET SPE may create fragments of unused bytes all over the SONET SPE. For efficient transport of variable-size IP packets, these unused bytes may be utilized for IP data.

Referring to FIG. 13, an operation 500 for CRC error checking is shown. If bit errors occur at an upstream node that receives a packet with a correct CRC, the downstream node will never learn about the bit errors if the upstream node recomputed CRC for the packet before transmission. When MPLS is used, a node that receives the packet usually swaps the label with a different

0325.00345
CD00025

value, pops the label, or adds a new label to the stack. If MPLS is embedded inside a packet, payload CRC will change at each node.

One solution would be to check for CRC for ingress, but not to re-compute the CRC on egress. An efficient way to implement such CRC computation is to separate header CRC from payload CRC. This way, header CRC is recomputed easily and quickly at intermediate nodes while the payload CRC is preserved end-to-end. With HDT, all header labels and other temporary information for the packet may be carried outside of the payload so the payload data/CRC is not modified at any of the intermediate nodes.

A SONET node may be a data-aware add/drop multiplexer, a digital cross-connect, or a router/access multiplexer sitting on a SONET ring. Such devices may implement HDT protocol for data encapsulation and transport over SONET and WDM networks. Traditional circuitry for ATM cell delineation, PPP processing and other protocol handling may be implemented similar to conventional approaches, with some additional added circuitry for HDT encapsulation and decapsulation. The path signal label (PSL) value proposed for use with the HDT may be the same as the one for SDL frames.

Referring to FIG. 14, an example of spatial reuse with HDT is shown. Spatial reuse of bandwidth across a number of network nodes (e.g., A, B, C, D) may be achieved by permitting full or partial termination of individual packets at any node. Spatial reuse of bandwidth reclaimed from the terminated packet may increase performance. HDT may provide an ideal way to achieve spatial reuse of SONET bandwidth. Using add/drop of hybrid data, nodes can reuse released bandwidth for transmission of any of the various kinds of data.

As the SONET SPEs are received at the nodes A, B, C, D, initial bytes may be placed in a small transit buffer. Through MPLS labels contained in the header section or through internal packet fields, a particular node A, B, C, D may be able to determine whether the packet belongs to the node. If the packet does not belong to the node, the bytes are streamed out of transit buffer to the output port. However, the packet may belong to the node A, B, C, D if, for example, (i) the D7 bit is set in the payload header, (ii) the packet area has been reserved for a fixed bandwidth channel such as a PDH, and/or (iii) in this case, the D3: D0 bits are not cleared. If the D7 bit is set to "0", the node may clear the D3: D0 field to mark the packets void and reusable, where

0325.00345
CD00025

the bytes belonging to the packet are sent to system. The number of bytes sent to the system may be specified in the length field of the SDL header. If the header shows fragmentation then a packet is received in many fragments and sent out to the system until the last fragment is received.

Packets may be added either using a fresh SONET SPE or by reusing bytes inside an incoming or previously queued frame. The decision of which packet to add to a void or reusable packet area inside an SPE can be made on following lines by (a) selecting a packet (or a collection of packets) that will fit inside the reusable area, (b) selecting all packets that can fit inside the reusable space, or (c) selecting a packet based on QoS parameters or packet priority. Since SONET frames repeat at 125ms intervals, packet transmission may be arranged to achieve a desired rate. Once a packet is selected for addition to the SPE, the node creates a payload header by setting payload type, reusability and other bits for the packet. The circuit 100 may then add the header to the payload.

The SDL framing mechanism may use length/CRC pair information as a header and a frame delimiter. SDL provides a robust scrambling and frame locator technique and may be used for

0325.00345
CD00025

direct data-over-fiber networks where SONET framing may not be used. Implementing OAM packets may eliminate the need for complex SONET framing and link management overheads. In the example of direct data-over-fiber networks, the HDT protocol structure may operate unmodified. Point-to-point WDM networks and ring-based SONET networks (or any other network) may easily be mixed and connected to each other. With a powerful support for MPLS (that may be transported independently of payload), networks may be designed that may have alternative LSP (Label Switched Paths) links for a highly robust redundancy. For example, nodes on a SONET ring may be connected through another network that may be entirely different from the ring. The backup path could be a high-speed point-to-point link or a ring network that may be geographically quite diverse. By providing a common network protocol engine, the HDT protocol may permit configuration of these networks quite easily without requiring complex protocol translation logic for different network configuration.

The present invention may use a packet payload header to identify the kind of packet inside. These identifier bits tell what kind of packet/protocol (e.g., such as Ethernet, PPP, IP, Frame Relay, ATM cells, T1, etc.) is inside the payload. Using

0325.00345
CD00025

such a technique, different protocols may be supported at two ends without the need for advanced provisioning. Using conventional methods, the use of a single protocol over a WAN needs to be negotiated.

5 The identifier may indicate whether one or more packet areas inside SONET SPE may be reused at an intermediate node. Conventional SONET networks require the SONET frame to travel around the ring until removed by the sender. Even when the receiving node received a packet, the frame went around the network, wasting bandwidth. With the present invention, not only may a receiver mark a SONET SPE as reusable, but different receivers on the fiber network may mark different sections of SONET SPE area as reusable when a packet is received by different receivers.

10
15
20
25
30
35
40
45
50
55
60
65
70
75
80
85
90
95
100
105
110
115
120
125
130
135
140
145
150
155
160
165
170
175
180
185
190
195
200
205
210
215
220
225
230
235
240
245
250
255
260
265
270
275
280
285
290
295
300
305
310
315
320
325
330
335
340
345
350
355
360
365
370
375
380
385
390
395
400
405
410
415
420
425
430
435
440
445
450
455
460
465
470
475
480
485
490
495
500
505
510
515
520
525
530
535
540
545
550
555
560
565
570
575
580
585
590
595
600
605
610
615
620
625
630
635
640
645
650
655
660
665
670
675
680
685
690
695
700
705
710
715
720
725
730
735
740
745
750
755
760
765
770
775
780
785
790
795
800
805
810
815
820
825
830
835
840
845
850
855
860
865
870
875
880
885
890
895
900
905
910
915
920
925
930
935
940
945
950
955
960
965
970
975
980
985
990
995
1000
1005
1010
1015
1020
1025
1030
1035
1040
1045
1050
1055
1060
1065
1070
1075
1080
1085
1090
1095
1100
1105
1110
1115
1120
1125
1130
1135
1140
1145
1150
1155
1160
1165
1170
1175
1180
1185
1190
1195
1200
1205
1210
1215
1220
1225
1230
1235
1240
1245
1250
1255
1260
1265
1270
1275
1280
1285
1290
1295
1300
1305
1310
1315
1320
1325
1330
1335
1340
1345
1350
1355
1360
1365
1370
1375
1380
1385
1390
1395
1400
1405
1410
1415
1420
1425
1430
1435
1440
1445
1450
1455
1460
1465
1470
1475
1480
1485
1490
1495
1500
1505
1510
1515
1520
1525
1530
1535
1540
1545
1550
1555
1560
1565
1570
1575
1580
1585
1590
1595
1600
1605
1610
1615
1620
1625
1630
1635
1640
1645
1650
1655
1660
1665
1670
1675
1680
1685
1690
1695
1700
1705
1710
1715
1720
1725
1730
1735
1740
1745
1750
1755
1760
1765
1770
1775
1780
1785
1790
1795
1800
1805
1810
1815
1820
1825
1830
1835
1840
1845
1850
1855
1860
1865
1870
1875
1880
1885
1890
1895
1900
1905
1910
1915
1920
1925
1930
1935
1940
1945
1950
1955
1960
1965
1970
1975
1980
1985
1990
1995
2000
2005
2010
2015
2020
2025
2030
2035
2040
2045
2050
2055
2060
2065
2070
2075
2080
2085
2090
2095
2100
2105
2110
2115
2120
2125
2130
2135
2140
2145
2150
2155
2160
2165
2170
2175
2180
2185
2190
2195
2200
2205
2210
2215
2220
2225
2230
2235
2240
2245
2250
2255
2260
2265
2270
2275
2280
2285
2290
2295
2300
2305
2310
2315
2320
2325
2330
2335
2340
2345
2350
2355
2360
2365
2370
2375
2380
2385
2390
2395
2400
2405
2410
2415
2420
2425
2430
2435
2440
2445
2450
2455
2460
2465
2470
2475
2480
2485
2490
2495
2500
2505
2510
2515
2520
2525
2530
2535
2540
2545
2550
2555
2560
2565
2570
2575
2580
2585
2590
2595
2600
2605
2610
2615
2620
2625
2630
2635
2640
2645
2650
2655
2660
2665
2670
2675
2680
2685
2690
2695
2700
2705
2710
2715
2720
2725
2730
2735
2740
2745
2750
2755
2760
2765
2770
2775
2780
2785
2790
2795
2800
2805
2810
2815
2820
2825
2830
2835
2840
2845
2850
2855
2860
2865
2870
2875
2880
2885
2890
2895
2900
2905
2910
2915
2920
2925
2930
2935
2940
2945
2950
2955
2960
2965
2970
2975
2980
2985
2990
2995
3000
3005
3010
3015
3020
3025
3030
3035
3040
3045
3050
3055
3060
3065
3070
3075
3080
3085
3090
3095
3100
3105
3110
3115
3120
3125
3130
3135
3140
3145
3150
3155
3160
3165
3170
3175
3180
3185
3190
3195
3200
3205
3210
3215
3220
3225
3230
3235
3240
3245
3250
3255
3260
3265
3270
3275
3280
3285
3290
3295
3300
3305
3310
3315
3320
3325
3330
3335
3340
3345
3350
3355
3360
3365
3370
3375
3380
3385
3390
3395
3400
3405
3410
3415
3420
3425
3430
3435
3440
3445
3450
3455
3460
3465
3470
3475
3480
3485
3490
3495
3500
3505
3510
3515
3520
3525
3530
3535
3540
3545
3550
3555
3560
3565
3570
3575
3580
3585
3590
3595
3600
3605
3610
3615
3620
3625
3630
3635
3640
3645
3650
3655
3660
3665
3670
3675
3680
3685
3690
3695
3700
3705
3710
3715
3720
3725
3730
3735
3740
3745
3750
3755
3760
3765
3770
3775
3780
3785
3790
3795
3800
3805
3810
3815
3820
3825
3830
3835
3840
3845
3850
3855
3860
3865
3870
3875
3880
3885
3890
3895
3900
3905
3910
3915
3920
3925
3930
3935
3940
3945
3950
3955
3960
3965
3970
3975
3980
3985
3990
3995
4000
4005
4010
4015
4020
4025
4030
4035
4040
4045
4050
4055
4060
4065
4070
4075
4080
4085
4090
4095
4100
4105
4110
4115
4120
4125
4130
4135
4140
4145
4150
4155
4160
4165
4170
4175
4180
4185
4190
4195
4200
4205
4210
4215
4220
4225
4230
4235
4240
4245
4250
4255
4260
4265
4270
4275
4280
4285
4290
4295
4300
4305
4310
4315
4320
4325
4330
4335
4340
4345
4350
4355
4360
4365
4370
4375
4380
4385
4390
4395
4400
4405
4410
4415
4420
4425
4430
4435
4440
4445
4450
4455
4460
4465
4470
4475
4480
4485
4490
4495
4500
4505
4510
4515
4520
4525
4530
4535
4540
4545
4550
4555
4560
4565
4570
4575
4580
4585
4590
4595
4600
4605
4610
4615
4620
4625
4630
4635
4640
4645
4650
4655
4660
4665
4670
4675
4680
4685
4690
4695
4700
4705
4710
4715
4720
4725
4730
4735
4740
4745
4750
4755
4760
4765
4770
4775
4780
4785
4790
4795
4800
4805
4810
4815
4820
4825
4830
4835
4840
4845
4850
4855
4860
4865
4870
4875
4880
4885
4890
4895
4900
4905
4910
4915
4920
4925
4930
4935
4940
4945
4950
4955
4960
4965
4970
4975
4980
4985
4990
4995
5000
5005
5010
5015
5020
5025
5030
5035
5040
5045
5050
5055
5060
5065
5070
5075
5080
5085
5090
5095
5100
5105
5110
5115
5120
5125
5130
5135
5140
5145
5150
5155
5160
5165
5170
5175
5180
5185
5190
5195
5200
5205
5210
5215
5220
5225
5230
5235
5240
5245
5250
5255
5260
5265
5270
5275
5280
5285
5290
5295
5300
5305
5310
5315
5320
5325
5330
5335
5340
5345
5350
5355
5360
5365
5370
5375
5380
5385
5390
5395
5400
5405
5410
5415
5420
5425
5430
5435
5440
5445
5450
5455
5460
5465
5470
5475
5480
5485
5490
5495
5500
5505
5510
5515
5520
5525
5530
5535
5540
5545
5550
5555
5560
5565
5570
5575
5580
5585
5590
5595
5600
5605
5610
5615
5620
5625
5630
5635
5640
5645
5650
5655
5660
5665
5670
5675
5680
5685
5690
5695
5700
5705
5710
5715
5720
5725
5730
5735
5740
5745
5750
5755
5760
5765
5770
5775
5780
5785
5790
5795
5800
5805
5810
5815
5820
5825
5830
5835
5840
5845
5850
5855
5860
5865
5870
5875
5880
5885
5890
5895
5900
5905
5910
5915
5920
5925
5930
5935
5940
5945
5950
5955
5960
5965
5970
5975
5980
5985
5990
5995
6000
6005
6010
6015
6020
6025
6030
6035
6040
6045
6050
6055
6060
6065
6070
6075
6080
6085
6090
6095
6100
6105
6110
6115
6120
6125
6130
6135
6140
6145
6150
6155
6160
6165
6170
6175
6180
6185
6190
6195
6200
6205
6210
6215
6220
6225
6230
6235
6240
6245
6250
6255
6260
6265
6270
6275
6280
6285
6290
6295
6300
6305
6310
6315
6320
6325
6330
6335
6340
6345
6350
6355
6360
6365
6370
6375
6380
6385
6390
6395
6400
6405
6410
6415
6420
6425
6430
6435
6440
6445
6450
6455
6460
6465
6470
6475
6480
6485
6490
6495
6500
6505
6510
6515
6520
6525
6530
6535
6540
6545
6550
6555
6560
6565
6570
6575
6580
6585
6590
6595
6600
6605
6610
6615
6620
6625
6630
6635
6640
6645
6650
6655
6660
6665
6670
6675
6680
6685
6690
6695
6700
6705
6710
6715
6720
6725
6730
6735
6740
6745
6750
6755
6760
6765
6770
6775
6780
6785
6790
6795
6800
6805
6810
6815
6820
6825
6830
6835
6840
6845
6850
6855
6860
6865
6870
6875
6880
6885
6890
6895
6900
6905
6910
6915
6920
6925
6930
6935
6940
6945
6950
6955
6960
6965
6970
6975
6980
6985
6990
6995
7000
7005
7010
7015
7020
7025
7030
7035
7040
7045
7050
7055
7060
7065
7070
7075
7080
7085
7090
7095
7100
7105
7110
7115
7120
7125
7130
7135
7140
7145
7150
7155
7160
7165
7170
7175
7180
7185
7190
7195
7200
7205
7210
7215
7220
7225
7230
7235
7240
7245
7250
7255
7260
7265
7270
7275
7280
7285
7290
7295
7300
7305
7310
7315
7320
7325
7330
7335
7340
7345
7350
7355
7360
7365
7370
7375
7380
7385
7390
7395
7400
7405
7410
7415
7420
7425
7430
7435
7440
7445
7450
7455
7460
7465
7470
7475
7480
7485
7490
7495
7500
7505
7510
7515
7520
7525
7530
7535
7540
7545
7550
7555
7560
7565
7570
7575
7580
7585
7590
7595
7600
7605
7610
7615
7620
7625
7630
7635
7640
7645
7650
7655
7660
7665
7670
7675
7680
7685
7690
7695
7700
7705
7710
7715
7720
7725
7730
7735
7740
7745
7750
7755
7760
7765
7770
7775
7780
7785
7790
7795
7800
7805
7810
7815
7820
7825
7830
7835
7840
7845
7850
7855
7860
7865
7870
7875
7880
7885
7890
7895
7900
7905
7910
7915
7920
7925
7930
7935
7940
7945
7950
7955
7960
7965
7970
7975
7980
7985
7990
7995
8000
8005
8010
8015
8020
8025
8030
8035
8040
8045
8050
8055
8060
8065
8070
8075
8080
8085
8090
8095
8100
8105
8110
8115
8120
8125
8130
8135
8140
8145
8150
8155
8160
8165
8170
8175
8180
8185
8190
8195
8200
8205
8210
8215
8220
8225
8230
8235
8240
8245
8250
8255
8260
8265
8270
8275
8280
8285
8290
8295
8300
8305
8310
8315
8320
8325
8330
8335
8340
8345
8350
8355
8360
8365
8370
8375
8380
8385
8390
8395
8400
8405
8410
8415
8420
8425
8430
8435
8440
8445
8450
8455
8460
8465
8470
8475
8480
8485
8490
8495
8500
8505
8510
8515
8520
8525
8530
8535
8540
8545
8550
8555
8560
8565
8570
8575
8580
8585
8590
8595
8600
8605
8610
8615
8620
8625
8630
8635
8640
8645
8650
8655
8660
8665
8670
8675
8680
8685
8690
8695
8700
8705
8710
8715
8720
8725
8730
8735
8740
8745
8750
8755
8760
8765
8770
8775
8780
8785
8790
8795
8800
8805
8810
8815
8820
8825
8830
8835
8840
8845
8850
8855
8860
8865
8870
8875
8880
8885
8890
8895
8900
8905
8910
8915
8920
8925
8930
8935
8940
8945
8950
8955
8960
8965
8970
8975
8980
8985
8990
8995
9000
9005
9010
9015
9020
9025
9030
9035
9040
9045
9050
9055
9060
9065
9070
9075
9080
9085
9090
9095
9100
9105
9110
9115
9120
9125
9130
9135
9140
9145
9150
9155
9160
9165
9170
9175
9180
9185
9190
9195
9200
9205
9210
9215
9220
9225
9230
9235
9240
9245
9250
9255
9260
9265
9270
9275
9280
9285
9290
9295
9300
9305
9310
9315
9320
9325
9330
9335
9340
9345
9350
9355
9360
9365
9370
9375
9380
9385
9390
9395
9400
9405
9410
9415
9420
9425
9430
9435
9440
9445
9450
9455
9460
9465
9470
9475
9480
9485
9490
9495
9500
9505
9510
9515
9520
9525
9530
9535
9540
9545
9550
9555
9560
9565
9570
9575
9580
9585
9590
9595
9600
9605
9610
9615
9620
9625
9630
9635
9640
9645
9650
9655
9660
9665
9670
9675
9680
9685
9690
9695
9700
9705
9710
9715
9720
9725
9730
9735
9740
9745
9750
9755
9760
9765
9770
9775
9780
9785
9790
9795
9800
9805
9810
9815
9820
9825
9830
9835
9840
9845
9850
9855
9860
9865
9870
9875
9880
9885
9890
9895
9900
9905
9910
9915
9920
9925
9930
9935
9940
9945
9950
9955
9960
9965
9970
9975
9980
9985
9990
9995
10000
10005
10010
10015
10020
10025
10030
10035
10040
10045
10050
10055
10060
10065
10070
10075
10080
10085
10090
10095
10100
10105
10110
10115
10120
10125
10130
10135
10140
10145
10150
10155
10160
10165
10170
10175
10180
10185
10190
10195
10200
10205
10210
10215
10220
10225
10

0325.00345
CD00025

same receiver to re-use a packet may help TDM channels and packet data within a single SPE.

Over time, bit definitions inside a payload header may change as further research is conducted on the fiber data protocol operation. Such changes in bit definitions are common in data communication protocols and do not change the nature and content of present invention.

The present invention often refers specifically to SONET. However, Synchronous Digital Hierarchy (SDH) protocols are equally appropriate. SDH is similar to SONET with differences in bit framing. These framing differences, however, do not change the discussion and scope of the present invention.

While the invention has been particularly shown and described with reference to the preferred embodiments thereof, it will be understood by those skilled in the art that various changes in form and details may be made without departing from the spirit and scope of the invention.